7. Electrical Parts List

7-1 DW21G5VDX/BWT

Level	Loc. No.	Code No.	Description ; Specification	Remark

ASSY CHASSIS

1		AA91-01670F	ASSY CHASSIS;DW21G5VDX/BWT	S.N.A
..2	C/B+H/	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
..2	CN002A	AA39-20497D	LEAD CONNECTOR ASSY;,1P,YFH800-01,RING,4	
..2	PCB+HC	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
..2		AA95-01814B	ASSY SUB-PCB,INTERFACE;DT21G5,V16ANTSC,A	S.N.A
...3	CN11	3708-001364	CONNECTOR-FPC/FFC/PIC;35P,1.25MM,STRAIGH	
...3	CN11A	3809-001180	CABLE-FLAT;30V,-30to+80C,80mm,35P,1.25mm	
...3	CN12	AA39-00230A	LEAD CONNECTOR ASSY;,10P,35023-0010,5100	
...3	CN13	3711-001018	CONNECTOR-HEADER;BOX,5P,1R,2mm,STRAIGHT,	
...3	CN14	AA39-00229A	LEAD CONNECTOR ASSY;,5P,35023-0005,51004	
...3	CND001	AA39-00180B	LEAD CONNECTOR ASSY;,14P,YBNH250-14,3515	
...3	CND002	AA39-00115C	LEAD CONNECTOR ASSY;,10P,YBNH250-10,3515	
...3	CND003	3711-003043	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
...3	CND004	3711-000682	CONNECTOR-HEADER;BOX,13P,1R,2mm,ANGLE,SN	
...3	CND03A	AA39-00153B	LEAD CONNECTOR ASSY;,4P,YBNH250-04,35155	
...3	ICD101	AA96-50162M	ASSY H/S;-,POWER,AA62-30013E,KA78R33	
....4		1203-001543	IC-VOLTAGE REGULATOR;78R33,TO-220,4P,400	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		AA62-30013E	HEAT-SINK,ES;-,A6063 EXTR,-,-,30(21) T02	S.N.A
...3	ICD103	1203-000122	IC-NEGA.FIXED REG.;7908,TO-220,3P,-,PLAS	
...3	JKD501	3707-001005	CONNECTOR-OPTICAL;PLUG,SM,-,4.4/2.0MM	S.N.A
...3	QD101	0502-000298	TR-POWER;KSD73,NPN,30000mW,TO-220,TP,120	
...3	QD102	0502-000298	TR-POWER;KSD73,NPN,30000mW,TO-220,TP,120	
...3	RD101	2006-001002	R-CEMENT;1.2ohm,5%,5W,CB,TP,9x13x25mm	
...3	RD103	2006-000162	R-CEMENT;2.7ohm,5%,5W,CB,BK,10x13x25.4m	
...3		AA97-05398A	ASSY AUTO-SUB;DT21G5,V16A,NTSC	S.N.A
....4	BD501	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	BD502	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	BDD101	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	BDD102	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	BDD103	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	BDD104	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	BDD105	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	BDD301	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4	CD101	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	CD102	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	CD103	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4	CD104	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	CD105	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	CD106	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	CD107	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4	CD109	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
....4	CD110	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	CD111	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
....4	CD112	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
....4	CD113	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
....4	CD114	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	CD115	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
....4	CD116	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	CD117	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	CD118	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
....4	CD119	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
....4	CD120	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	CD122	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	CD317	2401-002042	C-AL;220uF,20%,10V,GP,TP,6.3x11,5	
....4	CD318	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	CD325	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	CD326	2401-000914	C-AL;22uF,20%,16V,GP,TP,5x11,5	
....4	CD327	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m	
....4	CD328	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4	CD329	2401-000914	C-AL;22uF,20%,16V,GP,TP,5x11,5	
....4	CD505	2401-000914	C-AL;22uF,20%,16V,GP,TP,5x11,5	
....4	CD506	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	CD507	2301-000232	C-FILM,PEF;3.3nF,5%,50V,TP,8.1x4.5x13mm,	
....4	CD508	2201-000558	C-CERAMIC,DISC;0.47nF,10%,50V,Y5P,TP,5x3	
....4	CD509	2201-000558	C-CERAMIC,DISC;0.47nF,10%,50V,Y5P,TP,5x3	
....4	CD510	2301-000232	C-FILM,PEF;3.3nF,5%,50V,TP,8.1x4.5x13mm,	
....4	CD511	2201-000558	C-CERAMIC,DISC;0.47nF,10%,50V,Y5P,TP,5x3	
....4	CD512	2201-000558	C-CERAMIC,DISC;0.47nF,10%,50V,Y5P,TP,5x3	
....4	CD513	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
....4	CD514	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	CD515	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
....4	CD516	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	CD517	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
....4	CD518	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
....4	CD519	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	CD520	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
....4	CD521	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4	CD522	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
....4	CD523	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	CD601	2401-002009	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
....4	CD602	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
....4	CD603	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m	
....4	CD604	2202-000205	C-CERAMIC,MLC-AXIAL;22pF,5%,50V,SL,TP,1.	
....4	CD605	2202-000205	C-CERAMIC,MLC-AXIAL;22pF,5%,50V,SL,TP,1.	
....4	CD606	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	CD703	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
....4	DD101	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
....4	DD102	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
....4	DD501	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DD502	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DD505	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DD506	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DD507	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DD508	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DD509	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DD510	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DD601	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DD602	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DD603	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DD604	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DD706	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DD707	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DD708	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DD709	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DD710	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DD711	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DD712	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DD713	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	EYD01	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
....4	FLD501	2901-001125	FILTER-EMI ON BOARD;50V,0.5A,-,220pF,7x2	
....4	GTD01	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
....4	GTD02	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
....4	ICD102	1203-000293	IC-POSI.FIXED REG.;7808,TO-220,3P,-,PLAS	
....4	ICD602	1203-001274	IC-VOL. DETECTOR;7545,TO-92,3P,-,PLASTIC	
....4	LD501	2701-000112	INDUCTOR-AXIAL;100uH,10%,3x7mm	
....4	LD601	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4	PCB	AA41-00434A	PCB-INTERFACE;DW-28G5VD,FR-1,1L,A,1.6T,2	S.N.A
....4	QD103	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
....4	QD104	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
....4	QD501	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
....4	QD502	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
....4	QD503	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
....4	QD504	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
....4	QD505	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
....4	QD506	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
....4	QD507	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
....4	QD508	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
....4	QD509	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
....4	QD601	0501-000362	TR-SMALL SIGNAL;KSA2328A-Y,NPN,1W,TO-92L	
....4	QD602	0504-000116	TR-DIGITAL;KSR1001,NPN,300MW,4.7K/4.7K,T	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	QD603	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
....4	QD604	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
....4	RD102	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD106	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD107	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD111	2003-001036	R-METAL OXIDE(S);3.3ohm,5%,2W,AF,TP,3.9x	
....4	RD308	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD309	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD310	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD504	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD505	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD506	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD507	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD508	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD509	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD510	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD511	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD512	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD513	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD514	2001-000490	R-CARBON;200OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD515	2001-000490	R-CARBON;200OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD516	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD517	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD518	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD519	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD520	2001-000490	R-CARBON;200OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD521	2001-000490	R-CARBON;200OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD522	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD523	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD524	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD525	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD526	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD527	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD528	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD531	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD532	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD534	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD535	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD536	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD537	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD538	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD601	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD602	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD603	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD604	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD605	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD606	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD607	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD608	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD609	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD610	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD611	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD612	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD613	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD614	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD615	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD616	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD617	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD619	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD620	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD621	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD622	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD623	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD624	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD625	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD626	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD627	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD628	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD629	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD630	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD631	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD632	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD633	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD634	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD635	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD636	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD637	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD638	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD639	2001-000010	R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD640	2001-000832	R-CARBON;510OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD641	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD642	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD643	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD644	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD645	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD646	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD647	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD648	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD649	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD650	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD651	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD652	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD653	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD654	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD655	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD656	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD657	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD658	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD659	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD660	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD661	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD662	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD663	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD664	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD665	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD666	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD668	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD669	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD670	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD680	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD685	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	SWD601	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
....4	XTD601	2801-003750	CRYSTAL-UNIT;8MHZ,30PPM,28-AAA,22PF,80OH	
....4	ZDD101	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	ZDD601	0403-001373	DIODE-ZENER;MTZJ5.1A,4.81V-5.07V,500mW,D	
....4		AA97-06222A	ASSY SMD-SUB;DT21G5,V16A,NTSC	S.N.A
.....5	ICD302	1201-001419	IC-VIDEO AMP;7660,SSOP,16P,173MIL,TRIPLE	
.....5	ICD501	1002-001241	IC-D/A CONVERTER;AK4382VT,24BIT,TSSOP,16	
.....5	ICD502	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
.....5	ICD503	0801-000442	IC-CMOS LOGIC;74HCU04,INVERTER,SOP,14P,1	
.....5	ICD601	AA09-00197A	IC MICOM;SNM746-580,SNM746-580,64,1.8 TO	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2		AA95-01796A	ASSY SUB-PCB,CHROMA;DW21G6,C16A,PAL,AA95	
...3	BK201	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
...3	BK202	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
...3	C201	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
...3	C202	2309-000138	C-FILM,PE-PPF;100nF,5%,50V,TP,20x16x8.5,	
...3	C204	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
...3	C206	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
...3	C207	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
...3	C208	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
...3	C209	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
...3	C210	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
...3	C211	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
...3	C212	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
...3	C213	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
...3	C215	2203-002398	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,1608	
...3	C216	2203-002398	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,1608	
...3	C217	2203-002398	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,1608	
...3	C218	2203-002398	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,1608	
...3	C219	2203-002398	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,1608	
...3	C220	2203-002398	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,1608	
...3	C225	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
...3	C226	2203-000998	C-CERAMIC,CHIP;0.047nF,5%,50V,NP0,TP,160	
...3	C227	2203-000998	C-CERAMIC,CHIP;0.047nF,5%,50V,NP0,TP,160	
...3	C228	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
...3	C229	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
...3	C230	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
...3	C231	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
...3	C233	2401-002183	C-AL;220uF,20%,16V,GP,TP,8x9,5mm	
...3	C234	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
...3	C235	2301-000445	C-FILM,PEF;4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
...3	C236	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
...3	C237	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	

Level	Loc. No.	Code No.	Description ; Specification	Remark
...3	C238	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
...3	C250	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
...3	C259	2203-000851	C-CERAMIC,CHIP;0.039nF,5%,50V,NP0,TP,160	
...3	CN201	3711-002710	CONNECTOR-HEADER;NOWALL,15P,1R,2.5mm,ANG	
...3	CN202	3711-003543	CONNECTOR-HEADER;NOWALL,16P,1R,2.54mm,AN	
...3	CN203	3711-002647	CONNECTOR-HEADER;BOX,8P,1R,2.5mm,STRAIGH	
⚠ ...3	IC201S	1204-001740	IC-VIDEO PROCESS;TDA8889H,QFP,64P,-,PLAS	
...3	L202	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
...3	PCB	AA41-00456A	PCB-CHROMA;DW21G5,FR-4,2L,A,1.6T,180X245	S.N.A
...3	Q203	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
...3	R201	2007-000101	R-CHIP;82Kohm,5%,1/16W,DA,TP,1608	
...3	R203	2007-000129	R-CHIP;27Kohm,5%,1/16W,DA,TP,1608	
...3	R205	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
...3	R206	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
...3	R207	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
...3	R208	2007-000828	R-CHIP;39Kohm,1%,1/16W,DA,TP,1608	
...3	R209	2008-000206	R-FUSIBLE(S);1ohm,5%,1/2W,AF,TP,2.5x6.5m	
...3	R210	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
...3	R211	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
...3	R213	2007-001002	R-CHIP;510ohm,5%,1/16W,DA,TP,1608	
...3	R214	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
...3	R215	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
...3	R217	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
...3	R218	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
...3	R219	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
...3	R220	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
...3	R222	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
...3	R223	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
...3	R224	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
...3	R225	2007-000309	R-CHIP;10ohm,5%,1/16W,DA,TP,1608	
...3	R232	2007-001002	R-CHIP;510ohm,5%,1/16W,DA,TP,1608	
...3	R233	2008-000206	R-FUSIBLE(S);1ohm,5%,1/2W,AF,TP,2.5x6.5m	
...3	R234	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
...3	R235	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
...3	R236	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
...3	R237	2007-000129	R-CHIP;27Kohm,5%,1/16W,DA,TP,1608	
...3	R238	2007-000092	R-CHIP;15Kohm,5%,1/16W,DA,TP,1608	
...3	R240	2007-000309	R-CHIP;10ohm,5%,1/16W,DA,TP,1608	
...3	R261	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
...3	R262	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
...3	XT201	2801-003433	CRYSTAL-UNIT;12MHZ,30PPM,28-AAM,30PF,30O	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2		AA95-01781C	ASSY SUB-PCB,A/V;DW21G5,C16APAL,AA95-008	S.N.A
...3	CM50	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
...3	CM51	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
...3	CM52	2001-000309	R-CARBON;110OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	CM53	2001-000309	R-CARBON;110OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	CM54	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
...3	CM55	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
...3	CNM705	3711-000628	CONNECTOR-HEADER;-,11P,1R,2.5mm,STRAIGHT	
...3	CNM711	AA39-00070A	LEAD CONNECTOR-ASSY;,4P,YBNH250-04,35184	
...3	CNM712	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
...3	JAC701	3722-001031	JACK-PIN;3P,3.6mm,#18,AU	
...3	JAC702	3722-000143	JACK-PHONE;1P(VER),3.4PI,AG,BLK,NO	
...3	LM50	2001-000309	R-CARBON;110OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	LM51	2001-000309	R-CARBON;110OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	LM52	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
...3	LM53	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
...3	LM54	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
...3	LM55	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
...3	PCB	AA41-00354B	PCB-AV;SMD-21G5,FR-1,1L,B,1.6T,245x245,V	S.N.A
...3	RM50	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
...3	RM51	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
...3	WCNM70	AA39-20160D	LEAD CONNECTOR-ASSY;,11P,67096-011,S,600	
...3	WCNM71	AA39-20020D	LEAD CONNECTOR-ASSY;,5P,67096-005,S,600,	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2		AA95-01756D	ASSY SUB-PCB CRT;DW21G6,C16A21,PAL,AA95	S.N.A
...3	IC501	AA96-50311E	ASSY-H/S;-,-,AA62-30175D,TDA6108JF,-	S.N.A
....4		1201-001330	IC-VIDEO AMP;6108,ZSIP,9P,-,SINGLE,-,PLA	
....4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	S.N.A
....4		AA62-30175D	HEAT-SINK,PS;-,SECC,T1.0,-,33X15X30 FT-2	S.N.A
...3	PCB	AA41-00447C	PCB-CRT;DW21G5,FR-1,1L,C,1.6T,330X245,C1	S.N.A
...3	SC01	3722-001503	JACK-PIN;1P,1PI,NI,RED,SCR-JACK	
⚠ ...3	V999S	3704-000114	SOCKET-CRT;14P,29.1,35.5,SN,ISH09S/BK	
...3	WCN501	AA39-20030B	LEAD CONNECTOR-ASSY;,8P,67096-008,S,400,	
...3	WCN502	AA39-20029B	LEAD CONNECTOR-ASSY;,7P,67096-007,S,300,	
...3		AA97-05452A	ASSY AUTO-SUB;DW21G6,C16A,PAL,21	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	C504	2201-000723	C-CERAMIC,DISC;4.7nF,20%,3KV,Y5U,TP,16x5	
....4	C505	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m	
....4	C506	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m	
....4	C507	2301-001259	C-FILM,MPPF;100nF,5%,400V,TP,19x8x16,7.5	
....4	C508	2301-001259	C-FILM,MPPF;100nF,5%,400V,TP,19x8x16,7.5	
....4	C509	2202-000825	C-CERAMIC,MLC-AXIAL;680pF,10%,50V,Y5P,TP	
....4	CN501A	3711-002647	CONNECTOR-HEADER;BOX,8P,1R,2.5mm,STRAIGH	
....4	CN502A	3711-002646	CONNECTOR-HEADER;BOX,7P,1R,2.5mm,STRAIGH	
....4	D501	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D502	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D503	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D504	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
....4	D505	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D506	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D507	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DZ501	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ502	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ503	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ504	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	EL701	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
....4	EL702	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
....4	EL703	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
....4	EL704	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
....4	EL705	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
....4	EL706	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
....4	EL707	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
....4	EL708	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
....4	EL709	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
....4	EL710	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
....4	EL711	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
....4	EL712	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
....4	EL713	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
....4	EL714	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
....4	EY701	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
....4	GT501	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
....4	GT504	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
....4	L501	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	
....4	Q501	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	R504	2001-001102	R-CARBON(S);200OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R505	2001-001102	R-CARBON(S);200OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R506	2001-001102	R-CARBON(S);200OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R507	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R508	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R509	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4	R511	2001-000096	R-CARBON(S);1MOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R513	2008-000290	R-FUSIBLE(S);2.4ohm,5%,2W,AF,TP,3.9x10mm	
....4	R514	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R515	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R516	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2		AA95-01822C	ASSY SUB-PCB,MASTER;DW21G5,C16APAL,AA95-	S.N.A
...3	CN801	AA39-20179F	LEAD CONNECTOR-ASSY;,3(2)P,YFH800-150,S,	
...3	PCB	AA41-00355A	PCB-MASTER;DW21G5,FR-1,1L,A,1.6T,245x245	S.N.A
⚠ ...3	SW811S	3403-000179	SWITCH-PUSH;250V,5A,DPST,-,JPW-2104B	
...3		AA97-05250A	ASSY AUTO-SUB;DW21G5,C16A,PAL	S.N.A
....4	EY801	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
....4	EY802	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
....4	EY803	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
....4	EY804	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
....4	GT01A	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
....4	GT02A	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
....4	GT03A	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
....4	GT801	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
....4	GT802	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
....4	GT803	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
...3		AA61-10320A	BRACKET-MASTER;T3350,SECC,T1.0,-,-,-,-	S.N.A
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		6001-000057	SCREW-MACHINE;RH,+,M3,L6,ZPC(BLK),SWRCH1	S.N.A
..2		AA95-01844H	ASSY SUB-PCB,SOUND;DW28G5VD,21FDVD3,C16A	S.N.A
...3	BR01	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
...3	BR02	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
...3	CN601	3711-002706	CONNECTOR-HEADER;NOWALL,8P,1R,2.5mm,ANGL	
...3	CN602	3711-001283	CONNECTOR-HEADER;NOWALL,14P,1R,2.5mm,ANG	
...3	IC601	1204-001661	IC-SOUND PROCESSOR;MSP3411G-A2,DIP,52P,-	
...3	PCB	AA41-00435A	PCB-SOUND MODULE;DW-21G5VD,FR-1,1L,A,1.6	S.N.A
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA97-06486A	ASSY AUTO;DW28G5VD,C16A,21FDVD3,PAL,MSP	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	C605	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C606	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C607	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	C608	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
....4	C609	2201-000558	C-CERAMIC,DISC;0.47nF,10%,50V,Y5P,TP,5x3	
....4	C610	2201-000436	C-CERAMIC,DISC;0.002nF,0.25pF,50V,SL,TP,	
....4	C611	2201-000436	C-CERAMIC,DISC;0.002nF,0.25pF,50V,SL,TP,	
....4	C613	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
....4	C614	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
....4	C615	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
....4	C616	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
....4	C617	2201-000558	C-CERAMIC,DISC;0.47nF,10%,50V,Y5P,TP,5x3	
....4	C618	2201-000112	C-CERAMIC,DISC;1.5nF,10%,50V,Y5V,TP,5x3.	
....4	C619	2305-000354	C-FILM,MPEF;330nF,5%,50V,TP,7.3x4.8x5.5m	
....4	C620	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C621	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C622	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C623	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C624	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C625	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C626	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
....4	C627	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C628	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
....4	C629	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C630	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
....4	C631	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
....4	C632	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
....4	C633	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C634	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
....4	C635	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C636	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
....4	C637	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C638	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
....4	C639	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C640	2401-000914	C-AL;22uF,20%,16V,GP,TP,5x11,5	
....4	D601	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	L601	2701-000111	INDUCTOR-AXIAL;100uH,10%,2.5x3.4mm	
....4	L602	2701-000111	INDUCTOR-AXIAL;100uH,10%,2.5x3.4mm	
....4	L603	2701-000169	INDUCTOR-AXIAL;3.9uH,10%,2.5x3.4mm	
....4	L604	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	L605	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4	Q601	0501-000362	TR-SMALL SIGNAL;KSA2328A-Y,NPN,1W,TO-92L	
....4	R601	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R602	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R603	2001-000387	R-CARBON;16KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R604	2001-000387	R-CARBON;16KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R605	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R606	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R607	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R608	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R609	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R610	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R611	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R612	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R613	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R614	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R615	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R616	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R617	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R618	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R619	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	XT601	2801-003903	CRYSTAL-UNIT;18.432MHz,25ppm,28-AAM,12pF	
....4	ZD601	0403-001373	DIODE-ZENER;MTZJ5.1A,4.81V-5.07V,500mW,D	
...3		AA39-00047C	LEAD CONNECTOR-ASSY;,1P,JUMPER,BLK,100MM	
..2		AA96-20109B	ASSY-POWER,CORD;-,CP2/NO(4.0),H/C250,KKP	S.N.A
...3		3811-000401	WIRE-PVC CU;BCWA,300V,ROLL,17/0.16mm,#22	S.N.A
...3		AA39-10006X	POWER-CORD;-,KKP419C,KLCE-2F,2.286MT,3P,	
...3		AA61-20284A	HOLDER;P-CORD,PP,-,-,-,BLK,VO,KE-002	S.N.A
..2		AA98-00235A	ASSY-PCB,M/DVDP;,DVD-PMR25/BON,C16A,DW-2	
..2		AA61-00483C	HOLDER-CHASSIS;21G5,HIPS V0,-,-,-,G4309,	S.N.A
..2		AA90-02598D	ASSY COVER MISC-FRAME;21G5EX	S.N.A
...3	D/P+FD	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
...3	DECK+F	6003-001022	SCREW-TAPTITE;RH,+,B,M3,L12,ZPC(BLK),SWR	S.N.A
...3	DVD/P+	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
...3	O/P+FD	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
...3	SDT+FD	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
...3		AA65-00011B	CLAMP-WIRE;ALL MODEL,NYLON 66,V2,-,NTR,1	

Level	Loc. No.	Code No.	Description ; Specification	Remark
...3		AA63-00339B	SHIELD-DECK,TOP;21G5,SECC,T0.5,-,-,-,TOP	S.N.A
...3		AA61-00596B	FRAME-DECK;28G5,-,-,HIPS V0,BLK,-,-,-,MI	S.N.A
..2		AA91-00627A	ASSYDECK-M/DVDP;,2LD,MILLENO,DVD-DM002/B	S.N.A
..2		AA94-07580D	ASSY PCB MAIN;DW21G5VDX/BWT,C16A,RUSSIA	S.N.A
⚠ ...3	CR402S	2306-000357	C-FILM,MPPF;8.2nF,5%,1.6KV,BK,20x9.5x17.	
⚠ ...3	D812	AA96-00111T	ASSYH/S;-,POWER,AA62-30013L,FMG-G2CS,DW2	S.N.A
....4		0402-001230	DIODE-RECTIFIER;FMG-G2CS,1000V,3A,TO-220	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		AA62-30013L	HEAT-SINK,ES;-,-,-,-,44/22,-,WHT,-,-,-,-	S.N.A
...3	GT102A	AA39-20010B	LEAD CONNECTOR-ASSY;,1P,YFH800-01,S,500,	
...3	IC601	AA96-50398A	ASSY-H/S;-,-,AA62-30182E,TDA7297,-	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		1201-001064	IC-POWER AMP;7297,ZIP,15P,-,DUAL,32dB,PL	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		AA62-30182E	HEAT-SINK,ES;-,A6063 EXTR,-,WHT,-,-,-,40	S.N.A
⚠ ...3	IC801S	AA96-50373F	ASSY H/S;-,PWM,AA62-30181K,KA3A1265RD,IC	S.N.A
....4		AA62-30181K	HEAT-SINK,ES;-,AL6063 EXTR.,2,WHT,40MM,-	S.N.A
....4		AA61-10386A	BRACKET-IC;-,SECC 100,T1.0,-,-,-,KA2S068	S.N.A
....4		AA13-00101A	IC HYBRID;KA3S1265RD,CN5039,5PIN,-50TO12	S.N.A
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
⚠ ...3	IC802	AA96-00111U	ASSYH/S;-,POWER,AA62-30013L,KA78R08,TVDP	S.N.A
....4		1203-001697	IC-VOLTAGE REGULATOR;78R08,TO-220,4P,-,P	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		AA62-30013L	HEAT-SINK,ES;-,-,-,-,44/22,-,WHT,-,-,-,-	S.N.A
...3	IC901	AA09-00196A	IC MICOM;SPM742EW-464,SPM742EW-464,52P,3	
...3	IC904	1203-001752	IC-POSI.FIXED REG.;LF33CV,TO-220,3P,-,PL	
...3	JA701	3722-000195	JACK-SCART;42P,-,SN,BLK,NO	
...3	L405	AA27-10004B	COIL-CHOKE;-,1mH,10%,-,1.3A,BK,NY102K(1.	
⚠ ...3	LC801S	AA27-00113A	COIL DEGAUSSING;-,-,4.8mH,-,48T,9ohm,-,2	
⚠ ...3	LR401S	AA27-30003L	COIL-LINEARLITY;-,73uH,DR12x15,0.55mm,-,	
...3	Q401	AA96-00275A	ASSYH/S;-,COMPLEX,AA62-00051A,KSD5703,FM	S.N.A
....4		AA62-00051A	HEAT SINK-PS;-,-,-,SILVER,HOLE 31mm,ALL,	S.N.A
....4		AA60-30001A	WASHER-PLATE;M3,ID3.5,15X8.5,T1.0,-,SBHG	S.N.A
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		0502-001136	TR-POWER;KSD5703,NPN,70W,TO-3PF,ST,8-	
....4		0402-001296	DIODE-RECTIFIER;FMP-3FU,1.5KV,5A,TO-3PF,	
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	Q403	AA96-50305C	ASSYH/S;-,SOUND,AA62-30012E,IRF620,21G5	S.N.A
....4		0505-000156	FET-SILICON;IRF620,N,200V,5A,0.8ohm,50W,	
....4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4		AA62-30012E	HEAT-SINK,ES;-,A6063 EXTR,-,-,TO-220 H55	S.N.A
...3	R825	2006-001094	R-CEMENT;0.22OHM,5%,5W,CH,BK,27X9.5X9.5M	
⚠ ...3	T444S	AA26-00057A	TRANS-FBT;-,FUH-29A001B(S),25/29,130	
⚠ ...3	T801S	AA26-00142A	TRANS SWITCHING;,CS21S5T,160~300,PM5,PL7	
⚠ ...3	TU01S	AA40-00096A	TUNER;TCLS3101PD16A(N),PAL,181CH,38.9MHZ	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA97-03270A	ASSY ROBORT-MAIN;DW21G5VDX/BWT,C16A,RUS	S.N.A
....4	C407	2301-001338	C-FILM,MPE-PPF;0.68nF,5%,1.6kV,TP,28x7x1	
....4	C806	2401-002227	C-AL;330uF,20%,450V,GP,BK,35x45,10	
....4	CN201	3711-003052	CONNECTOR-HEADER;BOX,10P,1R,2.5MM,STRAIG	
....4	CN701	3711-000628	CONNECTOR-HEADER;-,11P,1R,2.5mm,STRAIGHT	
....4	CN901	3711-003975	CONNECTOR-HEADER;BOX,14P,1R,2.5mm,STRAIG	
⚠ 4	CR405S	2306-000188	C-FILM,MPPF;330nF,5%,400V,TP,26x19.5x11,	
⚠ 4	CX801S	2306-000321	C-FILM,MPPF;470NF,5%,275V,TP,-,22.5	
⚠ 4	CX802S	2306-000321	C-FILM,MPPF;470NF,5%,275V,TP,-,22.5	
⚠ 4	CY801S	2201-000446	C-CERAMIC,DISC;3.3nF,20%,400V,Y5U,TP,15x	
⚠ 4	CY802S	2201-000446	C-CERAMIC,DISC;3.3nF,20%,400V,Y5U,TP,15x	
⚠ 4	D801S	0402-001160	DIODE-BRIDGE;D5SB60,600V,6A,SIP-4,-	
⚠ 4	D805	AA96-00111C	ASSY-H/S;-,-,AA62-30013L,FML-G12S,-	S.N.A
.....5		0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-,-	
.....5		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
.....5		AA62-30013L	HEAT-SINK,ES;-,-,-,-,44/22,-,WHT,-,-,-,-	S.N.A
⚠ 4	D808	AA96-00111C	ASSY-H/S;-,-,AA62-30013L,FML-G12S,-	S.N.A
⚠ 4	FP801S	3601-000281	FUSE-CARTRIDGE;250V,4A,TIME-LAG,GLASS,5.	
....4	IC301	AA96-50406A	ASSY-H/S;-,-,AA62-30180K,LA7845,-	S.N.A
.....5		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
.....5		1204-000517	IC-VERTICAL DEF.;LA7845,SIP,7P,-,PLASTIC	
.....5		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
.....5		AA62-30180K	HEAT-SINK,ES;-,A6063 EXTR,-,WHT,50/13,-,	S.N.A
....4	IC701	1001-001114	IC-VIDEO SWITCH;TEA6425,VIDEO SWITCH ,DI	
⚠ 4	IC804	1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	
⚠ 4	IC805	1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	
....4	IC902	1103-001213	IC-EEPROM;M24C16-WBN6,2048x8Bit,SDIP,8P,	
⚠ 4	LX801S	AA29-30002N	FILTER-LINE NOISE;-,16MH,1.5A,AC100~260V	
⚠ 4	LX802S	AA29-30002N	FILTER-LINE NOISE;-,16MH,1.5A,AC100~260V	
⚠ 4	NT801S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	PC801S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	
....4	PT801S	1404-000002	THERMISTOR-PTC;9ohm,20%,-,-,TR,RECT,-	
....4	RL801S	3501-001040	RELAY-POWER;12VDC,500mW,10A,1FormA,15mS,	
....4	T401	AA26-50001R	TRANS-HORIZ.DRIVE;-,-,-,80MH,-,-,520UH,-	
....4		AA97-04635A	ASSY AUTO-MAIN;DW21G5VDX/BWT,C16A,RUSSIS.N.A	
.....5	C101	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
.....5	C102	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
.....5	C103	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
.....5	C104	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C105	2401-000133	C-AL;1000uF,20%,16V,GP,TP,10x20,5	
.....5	C106	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C108	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
.....5	C109	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
.....5	C201	2401-000133	C-AL;1000uF,20%,16V,GP,TP,10x20,5	
.....5	C301	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5	C302	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
.....5	C303	2201-002031	C-CERAMIC,DISC;0.005nF,0.5pF,50V,NP0,TP,	
.....5	C304	2305-000285	C-FILM,MPEF;220NF,5%,100V,TP,10.5X5.5X15	
.....5	C305	2305-001011	C-FILM,MPEF;22nF,5%,100V,TP,3.5x12.5x7.5	
.....5	C306	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
.....5	C307	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
.....5	C308	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C309	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5	C401	2201-000556	C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5.	
.....5	C402	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
.....5	C403	2201-000556	C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5.	
.....5	C404	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
.....5	C405	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C406	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
.....5	C408	2305-000382	C-FILM,MPEF;4.7nF,5%,400V,TP,-,5mm	
.....5	C411	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5	C412	2305-000178	C-FILM,MPEF;10nF,5%,100V,TP,-,5mm	
.....5	C414	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
.....5	C420	2301-001065	C-FILM,MPPF;47nF,5%,630V,TP,19x15.5x7,7.	
.....5	C421	2201-000556	C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5.	
.....5	C422	2401-001527	C-AL;47uF,20%,250V,HR,TP,13x25mm,5m	
.....5	C424	2201-000132	C-CERAMIC,DISC;0.1nF,10%,500V,Y5P,TP,6.5	
.....5	C427	2401-002267	C-AL;2.2uF,20%,250V,GP,TP,8x11.5,5	
.....5	C602	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C603	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C604	2401-001998	C-AL;1000uF,20%,25V,GP,TP,10x20,5mm	
.....5	C605	2401-002229	C-AL;470nF,20%,50V,WT,TP,5x11,5	
.....5	C606	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C607	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C608	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
.....5	C609	2401-000647	C-AL;2.2uF,20%,50V,BP,TP,5x11,5	
.....5	C610	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
.....5	C611	2401-000647	C-AL;2.2uF,20%,50V,BP,TP,5x11,5	
.....5	C612	2301-000445	C-FILM,PEF;4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
.....5	C701	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
.....5	C702	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
.....5	C703	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
.....5	C704	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
.....5	C705	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
.....5	C706	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
.....5	C709	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
.....5	C711	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
.....5	C715	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C716	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
.....5	C717	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
.....5	C803	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
.....5	C804	2201-000332	C-CERAMIC,DISC;2.2nF,20%,250V,Y5U,TP,9x4	
.....5	C807	2301-001397	C-FILM,PPF;2.2nF,5%,1.2kV,TP,15x8.5x13.5	
.....5	C808	2401-003046	C-AL;47uF,20%,50V,WT,TP,6.3x11,2.5	
.....5	C809	2301-000395	C-FILM,PEF;18NF,5%,50V,TP,6.5X12.5X3.5MM	
.....5	C810	2401-002594	C-AL;220uF,20%,16V,GP,TP,8x11.5,5	
.....5	C811	2305-000450	C-FILM,MPEF;56nF,5%,100V,TP,-,5mm	
.....5	C812	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C814	2201-000639	C-CERAMIC,DISC;0.68nF,10%,2kV,Y5P,TP,9x5	
.....5	C815	2401-000293	C-AL;100uF,+30-10%,200V,GP,TP,16x25	
.....5	C816	2401-003058	C-AL;100uF,20%,200V,WT,TP,16x25,7.5	
.....5	C817	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
.....5	C818	2401-002215	C-AL;2200uF,20%,25V,WT,TP,13x25,5	S.N.A
.....5	C820	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
.....5	C821	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5	C822	2401-003141	C-AL;2200uF,20%,25V,WT,TP,13x25,5mm	
.....5	C824	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
.....5	C825	2401-002215	C-AL;2200uF,20%,25V,WT,TP,13x25,5	S.N.A
.....5	C826	2401-002215	C-AL;2200uF,20%,25V,WT,TP,13x25,5	S.N.A
.....5	C827	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
.....5	C828	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
.....5	C829	2401-001998	C-AL;1000uF,20%,25V,GP,TP,10x20,5mm	
.....5	C830	2401-001998	C-AL;1000uF,20%,25V,GP,TP,10x20,5mm	
.....5	C831	2401-001428	C-AL;470uF,20%,50V,GP,TP,10x20,5	
.....5	C832	2401-001428	C-AL;470uF,20%,50V,GP,TP,10x20,5	
.....5	C833	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
.....5	C834	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
.....5	C835	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
.....5	C836	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
.....5	C839	2401-003034	C-AL;220uF,20%,16V,WT,TP,8x11.5,5	
.....5	C841	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
.....5	C842	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
.....5	C843	2201-000374	C-CERAMIC,DISC;0.22nF,5%,50V,NP0,TP,10.5	
.....5	C901	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
.....5	C904	2202-000791	C-CERAMIC,MLC-AXIAL;150pF,10%,50V,Y5P,TP	
.....5	C905	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
.....5	C906	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
.....5	C907	2401-003102	C-AL;100uF,20%,10V,GP,TP,5x11,5	
.....5	C908	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
.....5	C909	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
.....5	C910	2201-000980	C-CERAMIC,DISC;0.03nF,5%,50V,NP0,TP,5x3,	
.....5	C911	2201-000980	C-CERAMIC,DISC;0.03nF,5%,50V,NP0,TP,5x3,	
.....5	C912	2401-001914	C-AL;1uF,20%,50V,BP,TP,5x11,5	
.....5	C913	2401-003561	C-AL;1uF,10%,50V,GP,TP,5x11mm,5	
.....5	C914	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
.....5	C915	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
.....5	C917	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
.....5	CN502A	3711-002646	CONNECTOR-HEADER;BOX,7P,1R,2.5mm,STRAIGH	
.....5	CN602	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
.....5	CN901S	2503-000156	C-NETWORK;100pFx4,20%,50V	
.....5	CR403	2303-001001	C-FILM,PPF;22nF,5%,630V,TP,18x14.5x8.5mm	
.....5	D301	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
.....5	D305	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D307	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D401	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
.....5	D402	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
.....5	D403	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
.....5	D404	0402-000537	DIODE-RECTIFIER;RH1A,600V,0.6A,DO-204AC	
.....5	D405	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D406	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
.....5	D407	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D408	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
.....5	D409	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D410	0403-001316	DIODE-ZENER;MTZJ3.0A,2.85-3.07V,500mW,DO	
.....5	D411	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
.....5	D413	0402-000537	DIODE-RECTIFIER;RH1A,600V,0.6A,DO-204AC	
.....5	D415	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D601	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D602	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D603	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D604	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D605	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D801	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
.....5	D803	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
.....5	D804	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
.....5	D806	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D807	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
.....5	D809	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
.....5	D810	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
.....5	D811	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
.....5	D901	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D905	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D908	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	D909	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
.....5	DZ201	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
.....5	DZ302	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
.....5	DZ303	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
.....5	DZ304	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
.....5	DZ305	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
.....5	DZ306	0403-001167	DIODE-ZENER;MTZJ30D,30V,29.02-30.51V,500	
.....5	DZ601	0403-000719	DIODE-ZENER;MTZJ7.5B,7.5V,7.07-7.45V,500	
.....5	DZ602	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
.....5	DZ701	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
.....5	DZ702	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	

Level	Loc. No.	Code No.	Description ; Specification	Remark
	.....5 DZ703	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
	.....5 DZ801	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
	.....5 DZ802	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
	.....5 DZ803	0403-001167	DIODE-ZENER;MTZJ30D,30V,29.02-30.51V,500	
	.....5 DZ806	0403-001317	DIODE-ZENER;MTZJ3.0B,3.01-3.22V,500mW,DO	
	.....5 DZ808	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
	.....5 DZ902	0403-000510	DIODE-ZENER;MTZJ6.2B,6.2V,5.96-6.27V,500	
	.....5 DZ903	0403-000510	DIODE-ZENER;MTZJ6.2B,6.2V,5.96-6.27V,500	
	.....5 DZ904	0403-000510	DIODE-ZENER;MTZJ6.2B,6.2V,5.96-6.27V,500	
	.....5 DZ905	0403-000714	DIODE-ZENER;MTZJ3.3B,3.3V,3.32-3.53V,500	
	.....5 DZ906	0403-000510	DIODE-ZENER;MTZJ6.2B,6.2V,5.96-6.27V,500	
	.....5 DZ907	0403-000510	DIODE-ZENER;MTZJ6.2B,6.2V,5.96-6.27V,500	
	.....5 EL01	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
	.....5 EL02	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
	.....5 EL07	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
	.....5 EL10	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
	.....5 EL11	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
	.....5 EL12	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
	.....5 EL13	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
	.....5 EL14	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
	.....5 EL15	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
	.....5 EL16	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
	.....5 EL17	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
	.....5 EL18	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
	.....5 EL19	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
	.....5 EL20	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
	.....5 EL21	AA60-40011B	EYELET;ID2.2,OD3.2,-,-,BSP,-	S.N.A
	.....5 EY01	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY02	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY03	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY04	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY05	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY06	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY07	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY08	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY09	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY10	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY11	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY12	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY13	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY14	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY15	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY16	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY17	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY18	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY19	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY20	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY21	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY22	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY23	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY24	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY25	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY26	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY27	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY28	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY29	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY30	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY31	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY32	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY34	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY35	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY36	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY37	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY38	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY39	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY40	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY41	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY42	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY43	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY44	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY45	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY46	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY47	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY48	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY49	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY53	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY54	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY56	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY57	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY58	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY59	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY60	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY61	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY62	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY63	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY64	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY65	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY66	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY67	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY68	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY69	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY70	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY71	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY72	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY73	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY76	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY77	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY78	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY81	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY82	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY83	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY85	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY87	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY88	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY89	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY90	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY91	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY92	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY93	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY94	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY95	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY96	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY97	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY98	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 EY99	AA60-40011A	EYELET;ID2.0,OD2.8,-,-,BST,-	S.N.A
	.....5 F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
	.....5 F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
⚠	.....5 FA801S	3601-001163	FUSE-AXIAL LEAD;125V,7A,-,EPOXY,2.4X7.1M	S.N.A
⚠	.....5 FA802S	3601-001163	FUSE-AXIAL LEAD;125V,7A,-,EPOXY,2.4X7.1M	S.N.A
⚠	.....5 FA803S	3601-001163	FUSE-AXIAL LEAD;125V,7A,-,EPOXY,2.4X7.1M	S.N.A
	.....5 GT102	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
	.....5 GT103	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
	.....5 GT104	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
	.....5 GT301	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
	.....5 GT302	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
	.....5 GT402	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
	.....5 GT403	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
	.....5 GT601	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
	.....5 GT802	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
	.....5 GT803	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
	.....5 GT804	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
	.....5 GT805	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
	.....5 GT806	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
	.....5 GT811	AA60-40014A	PIN-GT,ASSY;1P,-,-,AUTO	S.N.A
	.....5 L101	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
	.....5 L203	2701-001034	INDUCTOR-AXIAL;22uH,10%,5x14mm	
	.....5 L205	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
	.....5 L206	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
	.....5 L208	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
	.....5 L301	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
	.....5 L302	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
	.....5 L303	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
	.....5 L304	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
	.....5 L305	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
	.....5 L406	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
	.....5 L407	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
	.....5 L601	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
	.....5 L602	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
	.....5 L603	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
	.....5 L606	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
	.....5 L607	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
	.....5 L608	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
	.....5 L609	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
	.....5 L610	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	L701	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L703	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L704	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L706	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
.....5	L707	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L708	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L709	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L710	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
.....5	L801	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
.....5	L802	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
.....5	L803	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
.....5	L804	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L808	2701-001007	INDUCTOR-AXIAL;24uH,10%,4.5x14mm	
.....5	L809	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
.....5	L813	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L814	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L815	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
.....5	L816	2701-001034	INDUCTOR-AXIAL;22uH,10%,5x14mm	
.....5	L901	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L902	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L903	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L904	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	L905	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5	PCB	AA41-00458C	PCB-MAIN;DW28G5,FR-1,1L,C,1.6T,330X245,C	S.N.A
.....5	Q402	0502-001007	TR-POWER;KSC2073-H2,NPN,25W,TO-220,ST,6	
.....5	Q601	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q701	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
.....5	Q702	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
.....5	Q704	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
.....5	Q802	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
.....5	Q803	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	
.....5	R101	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R102	2001-000309	R-CARBON;110OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R103	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R104	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R105	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R106	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R207	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R208	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R209	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R212	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R213	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R215	2001-001352	R-CARBON;620HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R216	2001-000745	R-CARBON;4.7OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R218	2001-000938	R-CARBON;680HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R301	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
.....5	R302	2004-001984	R-METAL(S);26.7Kohm,1%,1/2W,AA,TP,2.4x6.	
.....5	R303	2001-000016	R-CARBON(S);10HM,5%,1/2W,AA,TP,2.4X6.4MM	
.....5	R304	2003-000762	R-METAL OXIDE(S);6.8ohm,5%,2W,AF,TP,4x12	
.....5	R305	2003-000762	R-METAL OXIDE(S);6.8ohm,5%,2W,AF,TP,4x12	
.....5	R306	2008-001107	R-FUSIBLE(S);300ohm,5%,2W,AG,TP,3.9x12mm	
.....5	R309	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R310	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R314	2004-001986	R-METAL(S);35.7Kohm,1%,1/2W,AA,TP,2.4x6.	
.....5	R315	2004-001137	R-METAL;6.8Kohm,1%,1/8W,AA,TP,1.8x3.2m	
.....5	R402	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R403	2001-001155	R-CARBON(S);5.6KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R404	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R405	2008-001015	R-FUSIBLE(S);1.5ohm,5%,2W,AF,TP,3.9x10mm	
.....5	R407	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R408	2001-001142	R-CARBON(S);3KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R409	2001-001107	R-CARBON(S);220ohm,5%,1/2W,AA,TP,2.4x6.4	
.....5	R410	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R411	2001-001135	R-CARBON(S);36KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R412	2001-000020	R-CARBON(S);22OHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R413	2008-000266	R-FUSIBLE(S);1ohm,5%,2W,AF,TP,3.9x10mm	
.....5	R414	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R415	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R417	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R418	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R419	2001-001037	R-CARBON(S);0.39OHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R421	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R422	2001-000010	R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R423	2001-000085	R-CARBON(S);100KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R424	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
.....5	R425	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
.....5	R426	2003-002178	R-METAL OXIDE(S);1Kohm,5%,2W,AG,TP,3.9x1	
.....5	R427	2001-000531	R-CARBON;240KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R429	2001-001155	R-CARBON(S);5.6KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R430	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
.....5	R432	2004-001376	R-METAL(S);11Kohm,1%,1/2W,AA,TP,2.4x6.4m	
.....5	R434	2001-001107	R-CARBON(S);220ohm,5%,1/2W,AA,TP,2.4x6.4	
.....5	R435	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
.....5	R436	2003-002151	R-METAL OXIDE;18KOHM,5%,2W,AG,TP,6X16MM	
.....5	R601	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R602	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R603	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R604	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R605	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R606	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R607	2001-000010	R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R608	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R609	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R610	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R611	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R612	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R614	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R701	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R702	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R703	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R704	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R705	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R706	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R707A	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R708	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R709	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R710	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R711	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R714	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R715	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R716	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R717	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R718	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R720	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R721	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R722	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R723	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R724	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R725	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R726	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R801	2001-001103	R-CARBON(S);20KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R802	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
.....5	R803	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
.....5	R804	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
.....5	R805	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R806	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R807	2001-001148	R-CARBON(S);430OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R808	2001-001148	R-CARBON(S);430OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R809	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R810	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R811	2004-001408	R-METAL(S);91Kohm,1%,1/2W,AA,TP,2.4x6.4m	
.....5	R812	2006-001002	R-CEMENT;1.2ohm,5%,5W,CB,TP,9x13x25mm	
.....5	R813	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R814	2001-000085	R-CARBON(S);100KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R815	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R816	2001-001107	R-CARBON(S);220ohm,5%,1/2W,AA,TP,2.4x6.4	
.....5	R817	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R818	2001-001113	R-CARBON(S);270KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	R819	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
.....5	R821	2004-001889	R-METAL(S);127Kohm,1%,1/2W,AA,TP,2.5x6.5	
.....5	R823	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R824	2008-001011	R-FUSIBLE(S);0.18ohm,10%,2W,AF,TP,3.9x10	
.....5	R826	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R834	2001-000812	R-CARBON;5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R835	2003-002024	R-METAL OXIDE(S);91Kohm,5%,2W,AF,TP,3.9x	
.....5	R837	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	R838	2001-000812	R-CARBON;5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R839	2001-001148	R-CARBON(S);430OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R841	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R842	2001-000812	R-CARBON;5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R901	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R902	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R903	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
.....5	R904	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R906	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R908	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R909	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R910	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R913	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R914	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R915	2001-000539	R-CARBON;24KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R916	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R918	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R919	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R920	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R921	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R922	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R923	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R924	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R925	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R926	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R927	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R928	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R929	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R930	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R931	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R932	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R933	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R934	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R935	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R936	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R937	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R938	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R939	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R940	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	R941	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R942	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R943	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R944	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R945	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R946	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R947	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R948	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R949	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R950	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R951	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R952	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R953	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R955	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R957	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R958	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R961	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R962	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
⚠ 5	RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 5	RY801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 5	RY802S	2002-001013	R-COMPOSITION;4.7Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 5	VP801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
⚠ 5	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
.....5	X901	2801-003433	CRYSTAL-UNIT;12MHZ,30PPM,28-AAM,30PF,30O	
...3		AA65-30104B	CLAMP-WIRE;ALL MODEL,NYLON 66,V2,-,BLK,W	S.N.A
...3		AA65-30104C	CLAMP-WIRE;ALL MODEL,NYLON 66,V2,-,NTR,W	S.N.A
..2		AA95-01751A	ASSY SUB-PCB CONTROL;DW21G5,C16A,AA95-00	
...3	CND701	AA39-00207A	LEAD CONNECTOR ASSY;,13P,35023-0013,5100	
...3	CND703	AA39-00075A	LEAD CONNECTOR-ASSY;,8P,YBNH250-08,35184	
...3	CND704	3711-001128	CONNECTOR-HEADER;BOX,8P,1R,2.5mm,ANGLE,S	
...3	CND704	AA39-00159B	LEAD CONNECTOR ASSY;,8P,TUBE,5264-08,351	
...3	LDD701	0601-000385	LED;ROUND,RED,3mm,700nm	
...3	LDD71A	AA61-50044A	GUIDE-LED;-,ABS,-,-,-,BLK,V0,AIWA	
...3	PCB	AA41-00330A	PCB-TVDP CONTROL;SMD-21G5,FR-1,1L,A,1.6T	S.N.A
...3	PCB+HC	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
...3	RMD701	AA59-60002B	MODULE-REMOCON;-,ORC-50HF,38KHz,940mm,ME	
...3	SWD701	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWD702	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWD703	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWD704	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWD705	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWD707	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWD708	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWD709	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWD710	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	SWD711	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3		AA61-00586B	HOLDER-TOP;15X5,ABS,-,-,-,BLK,HB	S.N.A
...3		AA97-05247A	ASSY AUTO-SUB;DW21G5,C16A	S.N.A
....4	CD701	2401-002291	C-AL;47uF,20%,16V,GP,TP,6.3x5,5	
....4	CD702	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	QD701	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-	
....4	RD701	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD702	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RD703	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	ZDD701	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
....4	ZDD702	0403-000510	DIODE-ZENER;MTZJ6.2B,6.2V,5.96-6.27V,500	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A

ASSY COVER REAR

1	*	AA90-02001M	ASSY COVER REAR;DW21G5VDX/BWT	S.N.A
..2	BACK	AA60-00091A	SPACER-FELT;-,FELT,150X10,-,-,BLK,T0.35,	S.N.A
..2		AA65-30008A	CLAMP-CORD;-,PE,HB,-,BLK,-	S.N.A
..2		AA64-01330C	INLAY-BACK,DVD;21G5,PS SHEET,T0.5,-,-,BL	S.N.A
..2		AA64-01329C	INLAY-BACK,TV;21G5,PS SHEET,T0.5,-,-,BLK	S.N.A
..2		AA64-01322F	CABINET BACK;21G5,HIPS HB,G4309	

ASSY COVER FRONT

1	*	AA90-01838M	ASSY COVER FRONT;DW21G5VDX/BWT	S.N.A
..2	AV+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
..2	CB+CF	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CB+FD	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	DCP+CF	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
..2	KPP+CF	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
..2	RJ+CB	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	SPK+CF	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
..2	TKC+CF	6002-000522	SCREW-TAPPING;TH,+,2,M4,L15,ZPC(BLK),SWR	S.N.A
..2		AA91-00684A	ASSYHOLDERSPK;-,-,8OHM/5W,-,TVDPVETYPE,2	S.N.A
..2		AA91-00494N	ASSY CABINET FRONT;,21G5	
...3	CF+KCD	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
...3	CF+KCT	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
...3	SPK+CF	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
...3	WIN+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
...3		AA64-01325B	WINDOW REMOCON;21G5,PC V0,-,-,-,-,VIOLET	S.N.A
...3		AA64-01326B	INDICATOR LED;21G5,ACRYL,-,-,-,-,-	S.N.A
...3		AA64-01328B	DECORATION-FRONT;21G5,ABS HB,-,-,-,-,G36	
...3		AA64-01572C	KNOB-TV;21G5,ABS,-,-,-,HB,G3676,-,SV012P	S.N.A
...3		AA64-01763B	INLAY-BARRIER,FRONT;21G5,PVC,T0.4,-,-,-,	S.N.A
...3		AA65-00011C	CLAMP-WIRE;ALL MODEL,NYLON 66,V2,-,NTR,2	
...3		AA64-70123A	BADGE-BRAND;NEW,AL,-,-,L=50,FLAT,SILVER,	S.N.A
...3		AA61-60003J	SPRING-CS;-,SUS304,-,-,OD6,N7,OD6,-,-,-,	S.N.A
...3		AA64-00846D	INLAY AV;21G5,PS SHEET,T0.3,-,-,BLK,3P E	S.N.A
...3		AA64-01321M	CABINET-FRONT;21G5,HIPS,HB,G4309,SV012P+	
...3		AA64-01323B	KNOB-DVD;21G5,ABS HB,-,-,-,-,G3676,-,SV0	S.N.A
...3		AA64-01324B	KNOB POWER;21G5,ABS HB,-,-,-,-,G3676,-,S	S.N.A
..2		AA65-00009B	CLAMP-D,COIL;21A8,NYLON 66,V0,-,-,-	
..2		AA64-01934A	DOOR-TRAY,ASSY;21G5,ABS HB,G3676,LB017M	S.N.A
...3		AA64-01875B	DOOR-TRAY;21G5,ABS HB,G3676,LB017M	
..2		AA60-10050R	SCREW-ASSY;-,SWRCH18A,M5,L31.5,HH,+,WC,-	S.N.A

ASSY P/MATERIAL

1	*	AA92-03090M	ASSY P/MATERIAL;DW21G5VDX/BWT	S.N.A
..2		AA60-40006A	PIN-STAPLE;-,-,H18,33X17.8X2.4,-,AUTO	S.N.A

ASSY BOX

1	*	AA92-02927M	ASSY BOX;DW21G5VDX/BWT	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark

Level	Loc. No.	Code No.	Description ; Specification	Remark

ASSY LABEL

1	*	AA92-02804F	ASSY LABEL;DW21G5VDX/BWT	S.N.A

ASSY CRT

1	*	AA91-02614A	ASSY CRT;DW21G5VDX/BWT	
..2		AA91-02169D	ASSY CRT;A51QDX992X,21,0MG,BARE,AA03-00	S.N.A
...3		AA63-60028A	SPACER-DY;-,NEOPRENE,-,-,-,BLK,-,-,V0 W1	S.N.A
...3		AA27-00199A	DEFLECTION YOKE;21DF,CDY-MT2103S,ST-3,A5	
⚠ ...3		AA27-00002A	MAGNET-CONVERGENCE;-,JH291-SC-OB,29.1MM	S.N.A
...3		AA03-00317A	CRT COLOR;A51QDX992X,0MG,1.85MH,18.0MH,2	
..2		AA98-70014D	ASSY-TBC,WIRE(P);-,22 Q,NTSC,PAL,1P,TVI	S.N.A
...3		AA98-70015A	ASSY-TBC,WIRE(P);DP,22Q,AA98-70014D,1P,T	S.N.A

ASSY ACCESSORY

1	*	AA92-03200F	ASSY ACCESSORY;DW21G5VDX/BWT	S.N.A
..2	CN001A	3809-001122	CABLE-FLAT;30V,80C,250MM,35P,1.25MM,UL28	
..2		AA68-01402A	MANUAL-GOOD WILL LETTER;,CIS,B5,1PAGE,A/	S.N.A
..2		AA68-01917B	MANUAL USERS;DW28G5VD,RUS,W/P100(G),1,B5	
..2		AA68-01120A	MANUAL SERVICE;-,-,CIS,A4,6PAGE(FOLD),W/	S.N.A
..2		AA59-00204B	REMOCON;,TM66,TVDP,51,SILVER,S/S,L/GRAY,	

MEMO